TACENS

ORIS DUAL 100

2 in1 Universal Notebook and USB Devices Power Adapter for all usb devices.

Universal Notbook AC adapter for Laptop and LCD Monitor. Compatible with major notebook brands. Up to 100W power with dual input: AC & CAR 12V LINE

1- Fujitsu, Sony, Panasonic (6.0 *1.0)
2- Toshiba,,Lg (6.3 * 3.0)
3- Toshiba, Sotec, Panasonic, Sahrp, NEC, Gateway, Dell, AMS Tech, Averatec, Acer, Compaq, HP, IBM (5.5 * 2.5)
4- Panasonic, Sharp, BM, Compaq, Acer (5.5 * 1.7)
5- Acer (5.5 * 2.1)
6- HP, Compaq, Asus (4.8 * 1.7)
7- BenQ (4.0 * 1.7)
8- Sharp (3.5 * 1.3)
9- Para coche

- Rated input voltage (50-50Hz): AC 100-240 V , DC11V-15V
- Input rated current: 1.6AMP
- Input Power : 140W; Out Power: 100W
- Eficiency: >85%
- Output Voltage: DC 15V-24V
- Output Current: 6AMP(max)
- Output Current USB: 5V 1.5ª max
- Overload protection and Shor t circuit protection.

Dimensions:	144x 56 x 34mm
Input DC:	11V-15V 10 A max. For the car.
Input AC:	AC 100 to 240V 50/60Hz at 1.6A max
Output DC:	15V 16V 6A max /18V 19V 20V 21V 22V 24V with 100W max
USB DC:	5V with 1.5A
Weight:	500g

Tested to Comply With FCC Standards FOR HOME OR OFFICE USE

RoHS COMPLIANT

DESIGNED IN EUROPE

Features & Especifications